




GIRA

Power supply DC 12 V
flush-mounted
5219 00

Gira
Giersiepen GmbH & Co. KG
Electrical installation systems
P.O. Box 1220
42461 Radevormwald
Phone+49 (0) 2195 / 602 - 0
Fax +49 (0) 2195 / 602 - 191
www.gira.de
info@gira.de

108633929 32/17



 Operating instructions for flush-mounted power supply DC 12 V

Security instructions



Electrical devices may only be installed and connected by a qualified electrician.

Serious injury, for example caused by an electric shock, fire or material damage, is possible in case of improper installation. These instructions are part of the product and must remain with the end customer.

Functional description

The flush-mounted power supply DC 12 V is required for the use of the wireless indoor siren, the wireless repeater and the wireless operating unit.

Installation

1. Switch the mains voltage off.
2. Connect the power supply to the mains supply using screw terminals L and N.
3. Attach the support ring and fasten the device in the flush-mounted device box.
4. Switch on mains voltage.
5. Attach the wireless indoor siren, wireless repeater or wireless operating unit.

Technical data

Input voltage:	AC 230 V, 50/60 Hz
Input current:	0.3 A
Output voltage:	DC 12 V
Output current:	300 mA
Power consumption:	max. 4.8 W
Standby mode:	0.35 W
Ambient temperature:	-5 to +50 °C
Protection type:	IP20
Class:	II
Standard-compliant:	EN 61558-1

Warranty

The warranty is provided in accordance with statutory requirements via the retailer. Please submit or send faulty devices postage paid and with an error description to your sales representative (retailer / installation company / electrical contractor).

The salesperson will forward the devices to the Gira Service Centre